

10.15 Fault code list for the vehicle electronic control unit

Contents of fault	Display	SPN	FMI
The value of clutch pedal sensor is less than the regulated value	T3-055	3055	01
The value of clutch pedal sensor is more than regulated value	T3-055	3055	02
The clutch pedal switch does not change to the ON side	T3-151	3151	06
The clutch pedal switch does not change to the OFF side	T3-151	3151	07
The value of the forward oil pressure sensor is less than the regulated value	T3-056	3056	01
The value of the forward oil pressure sensor is more than the regulated value	T3-056	3056	02
Both the forward switch and the reverse switch for the shuttle shift are on	T3-152	3152	04
The forward oil pressure sensor is low when the controller gives an on output signal.	T3-351	3351	21
The reverse oil pressure switch is off when the controller gives an on output signal.	T3-352	3352	21
The forward oil pressure sensor is on for more than 500 milliseconds when the controller gives an off signal for more than two seconds	T3-351	3351	22
The reverse oil pressure sensor is on for more than 500 milliseconds when the controller gives an off signal for more than two seconds	T3-352	3352	22
The clutch pedal relay is off for more than one second when the clutch pedal switch is on	T3-151	3151	09
	T3-156	3156	08
The clutch pedal relay is on for more than one second when the clutch pedal switch is off	T3-151	3151	08
	T3-156	3156	09
The Hydrostatic Transmission (HST) pedal sensor is less than the regulated value. The standard value range is 189 to 795	T3-251	3251	01
The Hydrostatic Transmission (HST) pedal sensor is more than the regulated value. The standard value range is 189 to 795	T3-251	3251	02
The Hydrostatic Transmission (HST) pedal sensor is not the correct value	T3-251	3251	03
The Hydrostatic Transmission (HST) oil sensor is less than the regulated value	T3-252	3252	01
The Hydrostatic Transmission (HST) oil sensor is more than the regulated value	T3-252	3252	02
The Hydrostatic Transmission (HST) adjustment is not the correct value	T3-253	3253	03